

# ECE 401 Signal and Image Analysis

## Homework 5

UNIVERSITY OF ILLINOIS  
Department of Electrical and Computer Engineering

Assigned: 11/2/2022; Due: 11/9/2022  
Reading: *DSP First* Chapter 8

### Problem 5.1

Consider the signal  $x[n] = \delta[n] + \delta[n-2]$ . Plot the magnitude DTFT,  $|X(\omega)|$ , of this signal, for  $0 \leq \omega < 2\pi$ . Draw circles on your plot to show the frequency samples  $X[k]$  for a 4-point DFT.

### Problem 5.2

In this problem, we will repeat Hamming's famous calculation, that resulted in the Hamming window. Consider a slightly modified, even-symmetric raised-cosine window,

$$w_C[n] = \left( (1-a) + a \cos\left(\frac{2\pi n}{N}\right) \right) w_R[n]$$

where  $a$  is an arbitrary constant, whose value has not yet been determined, and  $w_R[n]$  is

$$w_R[n] = \begin{cases} 1 & -M \leq n \leq M \\ 0 & \text{otherwise} \end{cases}$$

and the total length of the window is  $N = 2M + 1$ . Recall that the DTFT of an even-symmetric rectangular window is

$$W_R(\omega) = D_N(\omega) = \frac{\sin(\omega N/2)}{\sin(\omega/2)}$$

- Use the linearity and frequency-shift properties of the DTFT to find  $W_C(\omega)$ , the DTFT of  $w_C[n]$ .
- Sketch  $W_C(\omega)$ , for  $0 \leq \omega \leq \frac{10\pi}{N}$ . Draw circles at the frequencies that would be sampled by an  $N$ -point DFT. Find the values of  $W_C[k]$  for all  $k$  in the range  $0 \leq k \leq N-1$ , as functions of  $a$  and  $N$ .
- Find  $W_C\left(\frac{5\pi}{N}\right)$  in terms of  $a$  and  $N$ , and then find the value of  $a$  that zeros it out,  $W_C\left(\frac{5\pi}{N}\right) = 0$ .

Note: in order to find the value of  $W_C\left(\frac{5\pi}{N}\right)$ , you will want to take advantage of the fact that, for small enough values of  $k$ ,

$$\frac{\sin(k\pi/2)}{\sin(k\pi/2N)} \approx \frac{\sin(k\pi/2)}{k\pi/2N} = \begin{cases} \pm \frac{2N}{k\pi} & k \text{ odd} \\ 0 & k \text{ even and nonzero} \end{cases}$$