

ECE 417 Multimedia Signal Processing

Homework 2

UNIVERSITY OF ILLINOIS
Department of Electrical and Computer Engineering

Assigned: Tuesday, 9/7/2021; Due: Thursday, 9/16/2021
Reading: [Strang, Section 6.1](#)

Problem 2.1

Let A be a 2×2 matrix, and let x be one of its elements. All of its other elements are known, and are given as:

$$A = \begin{bmatrix} x & 3 \\ -1 & 2 \end{bmatrix} \quad (2.1-1)$$

The eigenvalues of A are given by

$$\lambda = -\frac{b}{2a} \pm \frac{\sqrt{b^2 - 4ac}}{2a} \quad (2.1-2)$$

for some particular values of a , b , and c . Find a , b , and c , in terms of x , such that Equation (2.1-2) gives the eigenvalues of A .

Problem 2.2

Let A be a 2×2 matrix, and let x be one of its elements. All of its other elements are known, and are given as:

$$A = \begin{bmatrix} x & 3 \\ -1 & 2 \end{bmatrix} \quad (2.2-1)$$

Suppose that you are given one of its eigenvalues, λ , and you want to find the corresponding eigenvector. As you know, the scale of an eigenvector is arbitrary, so let's arbitrarily set its first element to 1: $\vec{v} = [1, v_2]^T$. Solve for its second element, v_2 , in terms of λ .

Problem 2.3

Suppose that A is a tall thin matrix (more rows than columns). Suppose that $A^\dagger = (A^T A)^{-1} A^T$ is its pseudo-inverse, and that $\vec{v}^* = A^\dagger \vec{b}$. Show that \vec{v}^* is the minimum-squared error solution to the equation $A\vec{v} \approx \vec{b}$, i.e., show that \vec{v}^* minimizes

$$E = \|A\vec{v} - \vec{b}\|_2^2$$

Problem 2.4

Suppose that A is a short fat matrix (more columns than rows). Suppose that $A^\dagger = A^T (A A^T)^{-1}$ is its pseudo-inverse, and that $\vec{v}^* = A^\dagger \vec{b}$. Show that \vec{v}^* satisfies the equation $A\vec{v}^* = \vec{b}$.