

UNIVERSITY OF ILLINOIS AT URBANA-CHAMPAIGN  
Department of Electrical and Computer Engineering

ECE 401 SIGNAL AND IMAGE ANALYSIS  
Spring 2021

**EXAM 2**

Monday, November 1, 2021

- This is a **CLOSED BOOK** exam.
- You are permitted one sheet of handwritten notes, 8.5x11.
- Calculators and computers are not permitted.
- Do not simplify explicit numerical expressions. The expression “ $e^{-5} \cos(3)$ ” is a MUCH better answer than “-0.00667”.
- If you’re taking the exam online, you will need to have your webcam turned on. Your exam will appear on Gradescope at exactly 1:00pm; you will need to photograph and upload your answers by exactly 2:00pm.
- There will be a total of 100 points in the exam. Each problem specifies its point total. Plan your work accordingly.
- You must **SHOW YOUR WORK** to get full credit.

Name: \_\_\_\_\_

## Convolution

$$h[n] * x[n] = \sum_{m=-\infty}^{\infty} h[m]x[n-m] = \sum_{m=-\infty}^{\infty} x[m]h[n-m]$$

## Frequency Response

$$H(\omega) = \sum_{n=-\infty}^{\infty} h[n]e^{-j\omega n}$$
$$h[n] * \cos(\omega n) = |H(\omega)| \cos(\omega n + \angle H(\omega))$$

## Rectangular Window and Ideal LPF

$$w_R[n] = \begin{cases} 1 & 0 \leq n \leq N-1 \\ 0 & \text{otherwise} \end{cases} \leftrightarrow W_R(\omega) = e^{-j\omega(N-1)/2} \frac{\sin(\omega N/2)}{\sin(\omega/2)}$$
$$h_{\text{ideal}}[n] = \frac{\omega_c}{\pi} \text{sinc}(\omega_c n) \leftrightarrow H_{\text{ideal}}(\omega) = \begin{cases} 1 & |\omega| < \omega_c \\ 0 & \text{otherwise} \end{cases}$$

## Hamming Window

$$w_H[n] = \begin{cases} 0.54 - 0.46 \cos\left(\frac{2\pi n}{N-1}\right) & 0 \leq n \leq N-1 \\ 0 & \text{otherwise} \end{cases}$$

1. (20 points) Consider the following filter:

$$h[n] = \begin{cases} 1 & -6 \leq n \leq 2 \\ 0 & \text{otherwise} \end{cases}$$

Sketch  $|H(\omega)|$  as a function of  $\omega$ , for  $-\pi < \omega < \pi$ . Label the amplitude at  $\omega = 0$ , and at least two of the frequencies at which  $|H(\omega)| = 0$ .

2. (20 points) Consider the following filter:

$$h[n] = \begin{cases} 1 & -6 \leq n \leq 2 \\ 0 & \text{otherwise} \end{cases}$$

Design a filter  $g[n]$  such that  $F(\omega)$  is real valued (i.e., its imaginary part is zero,  $\Im\{F(\omega)\} = 0$ ), where

$$f[n] = g[n] * h[n]$$

$$g[n] =$$

3. (20 points) The signal  $x(t) = \cos(2\pi 800t)$  is sampled at  $F_s = 8000$  samples/second, then processed by the filter

$$y[n] = \frac{1}{7} \sum_{m=-3}^3 x[n-m]$$

The resulting signal is  $y[n] = A \cos(\omega n + \theta)$ . What are  $A$ ,  $\omega$ , and  $\theta$ ?

$$A =$$

$$\omega =$$

$$\theta =$$

4. (20 points) Consider the system

$$y[n] = \frac{1}{4}x[n+2] + \frac{1}{2}x[n+1] + x[n] - x[n-1] - \frac{1}{2}x[n-2] - \frac{1}{4}x[n-3]$$

Sketch the impulse response of this system as a function of  $n$ , for  $-5 \leq n \leq 5$ . Clearly label the values of every nonzero sample.

5. (20 points) You want to approximate the following ideal bandpass filter:

$$H_{\text{ideal}}(\omega) = \begin{cases} 1 & 0.3\pi < |\omega| < 0.4\pi \\ 0 & \text{otherwise} \end{cases}$$

Design an FIR filter  $h[n]$  that is exactly 64 samples long, such that  $|H(\omega)| \approx |H_{\text{ideal}}(\omega)|$ . Window  $h[n]$  in such a way that the first sidelobe has a level of less than -40dB relative to the mainlobe.

$$h[n] =$$