

UNIVERSITY OF ILLINOIS AT URBANA-CHAMPAIGN  
Department of Electrical and Computer Engineering

ECE 498MH PRINCIPLES OF SIGNAL ANALYSIS  
Fall 2013

**FINAL EXAM**

Friday, December 13, 2013

- This is a **CLOSED BOOK** exam. You may use three pages (front and back) of your own notes, and you may use a calculator if you wish.
- There are a total of 200 points in the exam. Each problem specifies its point total. Plan your work accordingly.
- You must **SHOW YOUR WORK** to get full credit.

Problem	Score	Problem	Score
1		6	
2		7	
3		8	
4		9	
5		10	
Total		Total	

Name: \_\_\_\_\_

### Useful Angles

$\theta$	$\cos \theta$	$\sin \theta$	$e^{j\theta}$
0	1	0	1
$\pi/6$	$\sqrt{3}/2$	1/2	$\sqrt{3}/2 + j/2$
$\pi/4$	$\sqrt{2}/2$	$\sqrt{2}/2$	$\sqrt{2}/2 + j\sqrt{2}/2$
$\pi/3$	1/2	$\sqrt{3}/2$	$1/2 + j\sqrt{3}/2$
$\pi/2$	0	1	$j$
$\pi$	-1	0	-1
$3\pi/2$	1	-1	$-j$
$2\pi$	1	0	1

### Useful DTFTs

$$\begin{aligned}
 x[n] = a^n u[n] &\leftrightarrow X(\omega) = \frac{1}{1 - az^{-1}} \\
 x[n] = \delta[n - k] &\leftrightarrow X(\omega) = e^{-j\omega k} \\
 x[n] = e^{j\theta n} &\leftrightarrow X(\omega) = 2\pi\delta(\omega - \theta) \\
 x[n] = \left(\frac{\omega_c}{\pi}\right) \text{sinc}(\omega_c n) &\leftrightarrow X(\omega) = \begin{cases} 1 & |\omega| < \omega_c \\ 0 & \text{otherwise} \end{cases} \\
 x[n] = \begin{cases} 1 & |n| \leq M \\ 0 & \text{otherwise} \end{cases} &\leftrightarrow X(\omega) = \frac{\sin(\omega(2M + 1)/2)}{\sin(\omega/2)}
 \end{aligned}$$

**Problem 1 (20 points)**

$$6 \cos \left( 2\pi 1000 \left( t - \frac{1}{4000} \right) \right) + 6 \sin \left( 2\pi 1000 \left( t - \frac{1}{4000} \right) \right) = A \cos(\Omega t + \phi)$$

Find the following quantities:

$$A = \boxed{\phantom{0000}}$$

$$\Omega = \boxed{\phantom{0000}}$$

$$\phi = \boxed{\phantom{0000}}$$

NAME: \_\_\_\_\_

Final Exam

Page 4

**Problem 2 (20 points)**

A periodic signal  $x(t)$ , with period  $T_0$ , is given by

$$x(t) = \begin{cases} 1 & 0 \leq t \leq \frac{3T_0}{4} \\ 0 & \frac{3T_0}{4} < t < T_0 \end{cases}$$

The same signal can be expressed as a Fourier series:

$$x(t) = \sum_{k=-\infty}^{\infty} X_k e^{j2\pi kt/T_0}$$

Find  $|X_2|$ , the amplitude of the second harmonic.

**Problem 3 (20 points)**

A particular system generates an output  $y[n]$  from its input  $x[n]$  according to the following rule:

$$y[n] = \begin{cases} x[n] & n \text{ is even} \\ \frac{1}{2}(x[n-1] + x[n+1]) & n \text{ is odd} \end{cases}$$

(a) **(6 points)** Is the system linear? Give your reason.

(b) **(4 points)** Is the system causal? Give your reason.

NAME: \_\_\_\_\_

*Final Exam*

Page 6

(c) (**6 points**) Is the system time-invariant? Give your reason.

(d) (**4 points**) Is the system stable? Give your reason.

**Problem 4 (20 points)**

Find  $y[n] = h[n] * x[n]$ , where

$$x[n] = \cos(0.02\pi n), \quad h[n] = \begin{cases} 1 & |n| \leq 3 \\ 0 & |n| > 3 \end{cases}$$

What is  $y[n]$ ? Hint: Find  $H(\omega)$  first. In order to find the numerical value of your answer, you may find it useful to approximate  $\sin x \approx x$ , an approximation that works for small values of  $x$ .

**Problem 5 (20 points)**

Find  $y[n] = h[n] * x[n]$ , where

$$x[n] = \begin{cases} 1 & n \geq 0 \\ 0 & n < 0 \end{cases}, \quad h[n] = \begin{cases} 1 & |n| \leq 3 \\ 0 & |n| > 3 \end{cases}$$

What is  $y[n]$ ?



**Problem 6 (20 points)**

Suppose

$$x[n] = \cos\left(\frac{7\pi n}{21}\right), \quad y[n] = \begin{cases} x[n] & |n| \leq 10 \\ 0 & \text{otherwise} \end{cases}, \quad Y(\omega) = \sum_{n=-\infty}^{\infty} y[n]e^{-j\omega n}$$

Sketch  $Y(\omega)$  for  $-\pi \leq \omega \leq \pi$ . Specify the frequency and amplitude of at least one peak. Also, specify at least three particular frequencies  $\omega$  such that  $Y(\omega) = 0$ .

**Problem 7 (20 points)**

You have a  $250 \times 250$  image that you want to upsample to  $250 \times 1000$  without introducing any aliasing. If  $x[n]$  is a row of the original image, and  $y[n]$  is a row of the upsampled image, this task can be accomplished by

$$y[n] = \sum_{m=0}^{249} x[m]g[n - 4m]$$

Sketch  $g[n]$  as a function of  $n$ . Show the value of  $g[0]$ , and specify at least three particular sample indices,  $n$ , at which  $g[n] = 0$ .

NAME: \_\_\_\_\_

Final Exam

Page 11

**Problem 8 (20 points)**

An 8000Hz tone,  $x(t) = \cos(2\pi 8000t)$ , is sampled at  $F_s = \frac{1}{T} = 10,000$  samples/second in order to create  $x[n] = x(nT)$ . Sketch  $X(\omega)$  for  $0 \leq \omega \leq 2\pi$  (**note the domain!!**). Specify the frequencies at which  $X(\omega) \neq 0$ .

**Problem 9 (20 points)**

Suppose  $x[n]$  is a random signal with the following autocorrelation:

$$R_{xx}[\tau] = \frac{1}{16} \text{sinc}^2\left(\frac{\pi n}{4}\right) = \left(\frac{\sin(\pi n/4)}{\pi n}\right)^2$$

Suppose  $e[n] = x[n] - ax[n-1]$ , and you want to find  $a$  in order to minimize  $E[e^2[n]]$ . Find the numerical value of  $a$  (“numerical” in the sense that there are no variables in your answer, however, your answer may include constants like  $\pi$  and  $\sqrt{2}$ ).

**Problem 10 (20 points)**

Suppose  $y[n] = x[n] + v[n]$ .  $v[n]$  is zero-mean, unit-variance white noise uncorrelated with  $x[n]$ , and  $x[n]$  is a random signal whose power spectrum is given by

$$P_{xx}(\omega) = \begin{cases} \frac{\pi}{2} - |\omega| & |\omega| \leq \frac{\pi}{2} \\ 0 & \frac{\pi}{2} \leq |\omega| \leq \pi \end{cases}$$

Suppose  $z[n] = h[n] * y[n]$ . Find  $H(\omega)$  in order to minimize  $E[(z[n] - x[n])^2]$ .