

UNIVERSITY OF ILLINOIS AT URBANA-CHAMPAIGN
Department of Electrical and Computer Engineering

ECE 401 SIGNAL AND IMAGE ANALYSIS
Spring 2022

EXAM 1

Wednesday, September 28, 2022

- This is a **CLOSED BOOK** exam.
- You are permitted one sheet of handwritten notes, 8.5x11.
- Calculators and computers are not permitted.
- If you're taking the exam online, you will need to have your webcam turned on. Your exam will appear on Gradescope at exactly 1:00pm; you will need to photograph and upload your answers by exactly 2:00pm.
- There will be a total of 100 points in the exam. Each problem specifies its point total. Plan your work accordingly.
- You must **SHOW YOUR WORK** to get full credit.

Name: _____

NetID: _____

Phasors

$$A \cos(2\pi ft + \theta) = \Re \{ A e^{j\theta} e^{j2\pi ft} \} = \frac{1}{2} e^{-j\theta} e^{-j2\pi ft} + \frac{1}{2} e^{j\theta} e^{j2\pi ft}$$

Spectrum

$$\text{Scaling: } y(t) = Gx(t) = \sum_{k=-N}^N (Ga_k) e^{j2\pi f_k t}$$

$$\text{Add a Constant: } y(t) = x(t) + C = (a_0 + C) + \sum_{k \neq 0} a_k e^{j2\pi f_k t}$$

$$\text{Add Signals: If } f_k = f'_n = f''_m \text{ then } a_k = a'_n + a''_m$$

$$\text{Time Shift: } y(t) = x(t - \tau) = \sum_{k=-N}^N (a_k e^{-j2\pi f_k \tau}) e^{j2\pi f_k t}$$

$$\text{Frequency Shift: } y(t) = x(t) e^{j2\pi Ft} = \sum_{k=-N}^N a_k e^{j2\pi (f_k + F)t}$$

$$\text{Differentiation: } y(t) = \frac{dx}{dt} = \sum_{k=-N}^N (j2\pi f_k a_k) e^{j2\pi f_k t}$$

Fourier Series

$$\text{Analysis: } X_k = \frac{1}{T_0} \int_0^{T_0} x(t) e^{-j2\pi kt/T_0} dt$$

$$\text{Synthesis: } x(t) = \sum_{k=-\infty}^{\infty} X_k e^{j2\pi kt/T_0}$$

Sampling and Interpolation:

$$x[n] = x\left(t = \frac{n}{F_s}\right)$$

$$f_a = \min(f \bmod F_s, -f \bmod F_s)$$

$$z_a = \begin{cases} z & f \bmod F_s < -f \bmod F_s \\ z^* & f \bmod F_s > -f \bmod F_s \end{cases}$$

$$y(t) = \sum_{n=-\infty}^{\infty} y[n] p(t - nT_s)$$

1. (25 points) Suppose that

$$x(t) = -12 \cos\left(1000\pi t - \frac{\pi}{4}\right) + 4 \sin(1000\pi t) = M \cos(1000\pi t + \theta)$$

Find x and y such that $M = \sqrt{x^2 + y^2}$ and either $\theta = \text{atan}(y/x)$ or $\theta = \text{atan}(y/x) - \pi$.

2. (25 points) $x(t)$ is a signal with a period of 0.01 seconds, and with the following shape:

$$x(t) = \begin{cases} 1 & 0 < t < 0.001 \\ 0 & 0.001 < t < 0.005 \\ -1 & 0.005 < t < 0.006 \\ 0 & 0.006 < t < 0.01 \end{cases}$$

- (a) What are the Fourier series coefficients X_k for $k \neq 0$? Your answer should contain no variables other than k , but you don't need to simplify.

- (b) Suppose that $y(t)$ is a signal such that $x(t) = \frac{dy}{dt}$. Express the Fourier series coefficients Y_k in terms of the Fourier series coefficients X_k . Note that you don't need to solve part (a) in order to solve this part of the problem.

3. (25 points) Suppose $x(t)$ is sampled to create the signal $y[n] = x\left(\frac{n}{F_s}\right)$, with a sampling frequency of $F_s = 10,000$ samples/second. The signal $y[n]$ is then passed through an ideal D/A in order to produce the signal $z(t)$. In each of the two following cases, what is $z(t)$?

(a)

$$x(t) = 3 \cos\left(2\pi 8000t + \frac{\pi}{4}\right)$$

What is $z(t)$?

(b)

$$x(t) = 3 \cos \left(2\pi 12,000t + \frac{\pi}{4} \right)$$

What is $z(t)$?

4. (25 points) Suppose that

$$x[n] = \sin\left(\frac{\pi n}{2}\right) = \begin{cases} 1 & n \text{ is odd, and } \frac{n-1}{2} \text{ is even} \\ -1 & n \text{ is odd, and } \frac{n-1}{2} \text{ is odd} \\ 0 & \text{otherwise} \end{cases}$$

You would like to generate a continuous-time audio signal, $y(t)$, using the interpolation formula

$$y(t) = \sum_{n=-\infty}^{\infty} x[n]g(t-n)$$

In each of the following cases, specify the value of $y(t)$ over the range $0 \leq t \leq 4$. You may specify $y(t)$ by drawing a plot of the function (if your plot clearly shows the value at each point in time in the range $0 \leq t \leq 4$), or by using an equation or a set of cases.

(a) What is $y(t)$ if

$$g(t) = \begin{cases} 1 & -\frac{1}{2} \leq t \leq \frac{1}{2} \\ 0 & \text{otherwise} \end{cases}$$

(b) What is $y(t)$ if

$$g(t) = \begin{cases} 1 - |t| & |t| \leq 1 \\ 0 & \text{otherwise} \end{cases}$$

(c) What is $y(t)$ if

$$g(t) = \begin{cases} 1 & t = 0 \\ \frac{\sin(\pi t)}{\pi t} & \text{otherwise} \end{cases}$$