

# ECE 401 Signal and Image Analysis

## Homework 3

UNIVERSITY OF ILLINOIS  
Department of Electrical and Computer Engineering

Assigned: 9/25/2023; Due: 10/4/2023  
Reading: *DSP First* Chapter 5

### Problem 3.1

In MP3, one of the filters you'll create is a local averaging filter. A local averaging filter produces an output  $y[n]$ , at time  $n$ , which is the average of the previous  $N$  samples of  $x[m]$ :

$$y[n] = \sum_{m=-\infty}^{\infty} h[m]x[n-m] \quad (3.1-1)$$

$$h[m] = \begin{cases} \frac{1}{N} & 0 \leq m \leq N-1 \\ 0 & \text{otherwise} \end{cases} \quad (3.1-2)$$

- (a) First, consider what happens if  $x[m]$  is a pure tone with a period of  $N_0 = \frac{2\pi}{\omega_0}$ , an amplitude of  $A$ , and a phase of  $\theta$ :

$$x[n] = A \cos(\omega_0 n - \theta)$$

Suppose that the averaging window,  $N$ , is exactly an integer multiple of  $N_0$ . For example, suppose that  $N = 3N_0$ . Draw a picture of  $x[n]$  as a function of  $n$ , and shade in the regions that would be added together by the summation in Eq. (3.1-1) in order to compute  $y[0]$ . Argue based on your figure (with no calculations at all) that  $y[0] = 0$ .

- (b) Adding up the samples of a cosine is easy when  $N$  is an integer multiple of  $N_0$ , but hard otherwise. It's actually much easier to add the samples of a complex exponential, because we can use the standard geometric series formula ([https://en.wikipedia.org/wiki/Geometric\\_series#Formula](https://en.wikipedia.org/wiki/Geometric_series#Formula)). Use that formula to find  $y[N-1]$  when

$$x[n] = e^{j\omega_0 n}$$

Your result should have the form  $y[0] = (1-a)/(1-b)$  for some complex-valued constants,  $a$  and  $b$ , that depend on  $\pi$ ,  $N$ , and  $\omega_0$ , but not on  $m$  or  $n$ .

### Problem 3.2

Another of the filters you'll create in MP3 is a backward-difference filter. A backward-difference filter is one of several different ways of approximating a first-derivative:

$$y[n] = \sum_{m=-\infty}^{\infty} h[m]x[n-m] \quad (3.2-1)$$

$$h[m] = \begin{cases} 1 & m = 0 \\ -1 & m = 1 \\ 0 & \text{otherwise} \end{cases} \quad (3.2-2)$$

- (a) First, consider what happens if  $x[m]$  is a pure tone with a period of  $T_0 = \frac{2\pi}{\omega_0}$ , an amplitude of  $A$ , and a phase of  $\theta$ :

$$x[n] = A \cos(\omega_0 n - \theta) \quad (3.2-3)$$

Plug Eq. (3.2-3) into Eq. (3.2-1), then use the following trigonometric identity and the following approximation to discover in exactly what way the first-difference operator approximates a derivative:

$$\begin{aligned} -2 \sin(a) \sin(b) &= \cos(a + b) - \cos(a - b) \\ \sin(b) &\approx b \quad \text{if } b \text{ is small} \end{aligned}$$

In order to apply the approximation, you can assume that  $\omega_0$  is a small number.

- (b) Let's try the same thing with a complex exponential. Plug the following value of  $x[n]$  into Eq. (3.2-1)

$$x[n] = e^{j\omega_0 n},$$

then assume that  $\omega_0$  is a small number, and simplify using the approximation

$$e^\phi \approx 1 + \phi \quad \text{if } \phi \text{ is small}$$

in order to get something that looks like  $dx[n]/dn$ .