




ECE329: Tutorial Session 8

November 6th, 2025



Wave Reflection & Transmission

TEM wave incident normally on a boundary

$$\tilde{E}_i(x) = -E_0 e^{-\alpha_1 x} e^{-j\beta_1 x} \hat{y}$$

$$\tilde{H}_i(x) = -\frac{E_0}{\eta_1} e^{-\alpha_1 x} e^{-j\beta_1 x} \hat{z}$$

$$\sigma_1, \mu_1, \epsilon_1 \\ x < 0$$

$$x = 0$$

$$\sigma_2, \mu_2, \epsilon_2 \\ x > 0$$

What to enforce?

$$\tilde{E}_i(x) = -E_0 e^{-\alpha_1 x} e^{-j\beta_1 x} \hat{y}$$

$$\tilde{H}_i(x) = -\frac{E_0}{\eta_1} e^{-\alpha_1 x} e^{-j\beta_1 x} \hat{z}$$

$$\tilde{E}_r(x) = -E_0 \Gamma e^{\alpha_1 x} e^{j\beta_1 x} \hat{y}$$

$$\tilde{H}_r(x) = \frac{E_0}{\eta_1} \Gamma e^{\alpha_1 x} e^{j\beta_1 x} \hat{z}$$

$$\sigma_1, \mu_1, \epsilon_1 \\ x < 0$$

$$x = 0$$

$$\tilde{E}_t(x) = -E_0 \tau e^{-\alpha_2 x} e^{-j\beta_2 x} \hat{y}$$

$$\tilde{H}_t(x) = -\frac{E_0}{\eta_2} \tau e^{-\alpha_2 x} e^{-j\beta_2 x} \hat{z}$$

$$\sigma_2, \mu_2, \epsilon_2 \\ x > 0$$

Coefficients

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1}$$

$$\tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$

Check our work:

1. What if $\eta_1 = \eta_2$?

2. What if $\eta_2 = 0$?



Problem 1

A wave propagates through free space and is normally incident upon a perfect dielectric with $\epsilon = 16\epsilon_0$ and $\mu = \mu_0$. What are Γ and τ ?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$



Problem 2

A single delta wave pops into existence at $t = 0$ halfway between the plates and moves to the right with amplitude 1000. Assume the area between the plates is free space.

Where is the wave at $t = 1\text{s}$?

What will its amplitude be?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$




Problem 2

A single delta wave pops into existence at $t = 0$ halfway between the plates and moves to the right with amplitude 1000. Assume the area between the plates is free space.

When will the wave be at $x = 2.25 \cdot 10^8 \text{m}$?

What will its amplitude be?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$




Problem 3

A single delta wave pops into existence at $t = 0$ in the middle and moves to the right with amplitude 1000. Assume the area between the plates is free space.

Where is the wave at $t = 1\text{s}$? What will its amplitude be?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$




Problem 3

A single delta wave pops into existence at $t = 0$ in the middle and moves to the right with amplitude 1000. Assume the area between the plates is free space.

Where is the wave at $t = 5.25\text{s}$? What will its amplitude be?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$




Problem 3

A single delta wave pops into existence at $t = 0$ in the middle and moves to the right with amplitude 1000. Assume the area between the plates is free space.

When will the wave be at $x = 2.25 \cdot 10^8 \text{m}$? What will its amplitude be?

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1} \quad \tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$



Standing Waves (dielectric to PEC)

$$\tilde{E}_i(y) = -E_0 e^{-j\beta_1 y} \hat{x}$$

$$\tilde{E}_r(y) = E_0 e^{j\beta_1 y} \hat{x}$$

Problem 1: Standing Waves

A wave propagates through an imperfect dielectric and is normally incident upon a perfect electrical conductor. Is a standing wave created in the imperfect dielectric?

$$\tilde{E}_i(y) = -E_0 e^{-\alpha_1 y} e^{-j\beta_1 y} \hat{x}$$

$$\tilde{E}_r(y) = -E_0 \Gamma e^{\alpha_1 y} e^{j\beta_1 y} \hat{x}$$




Transmission Lines!


Why do we care?



Transmission Line




Transmission Line: Parallel Plate Version




*** $\vec{E}$ and $\vec{H}$ should be pointing the opposite direction oops

Transmission Line: Parallel Plate Version



Coax Version:



Midterm 1 equations, in one place

$$\vec{F} = \frac{q_1 q_2}{4\pi\epsilon_0 r^2} \hat{r}$$

$$\vec{F} = q_1 \vec{E} + q_1 (\vec{v}_1 \times \vec{B})$$

$$\vec{E} = \frac{q_2}{4\pi\epsilon_0 r^2} \hat{r}$$

$$\hat{n} \cdot (\vec{D}_1 - \vec{D}_2) = \rho_s$$

$$\hat{n} \times (\vec{E}_1 - \vec{E}_2) = 0$$

$$\hat{n} \cdot (\vec{P}_1 - \vec{P}_2) = -\rho_{b,s}$$

$$\epsilon \oint \vec{E} \cdot d\vec{S} = Q_{\text{enclosed}}$$

$$\oint \vec{D} \cdot d\vec{S} = Q_{\text{enclosed}}$$

$$\iiint \rho dV = Q_{\text{enclosed}}$$

$$\oint \vec{B} \cdot d\vec{S} = 0$$

$$I = \oint \vec{J} \cdot d\vec{S} = -\frac{\partial Q_{\text{enclosed}}}{\partial t}$$

$$\epsilon = \epsilon_0(1 + \chi_e)$$

$$\vec{P} = \epsilon_0 \chi_e \vec{E}$$

$$\vec{D} = \epsilon_0 \vec{E} + \vec{P} = \epsilon \vec{E}$$

$$\vec{J} = \sigma \vec{E}$$

$$\rho_b = -\nabla \cdot \vec{P}$$

$$\nabla \cdot \epsilon_0 \vec{E} = \rho_f + \rho_b$$

$$\nabla \cdot \vec{D} = \rho$$

$$\nabla \cdot \vec{J} = -\frac{\partial \rho}{\partial t}$$

$$-\nabla^2 V = \frac{\rho}{\epsilon}$$

$$\nabla \times \vec{E} = 0$$

$$\vec{E} = -\nabla V$$

$$\oint \vec{E} \cdot d\vec{l} = 0$$

$$V_{ab} = V(b) - V(a) = -\int_a^b \vec{E} \cdot d\vec{l}$$

$$\oint \vec{D} \cdot d\vec{S} = \iiint \nabla \cdot \vec{D} dV$$

$$\oint \vec{E} \cdot d\vec{l} = \iint (\nabla \times \vec{E}) \cdot d\vec{S}$$

$$\int_a^b \nabla V \cdot d\vec{l} = V(b) - V(a)$$



Midterm 2 equations, in one place

$$\vec{B} = \frac{\mu I}{2\pi r} \hat{\phi}$$

$$d\vec{B} = \frac{\mu I d\vec{\ell} \times \hat{r}}{4\pi r^2}$$

$$\oint_C \vec{H} \cdot d\vec{\ell} = \iint_S \vec{J} \cdot d\vec{S}$$

$$\oint_C \vec{B} \cdot d\vec{\ell} = \mu I_{\text{encl}}$$

$$\nabla \times \vec{H} = \vec{J} + \frac{\partial \vec{D}}{\partial t}$$

$$\nabla \cdot \vec{B} = 0$$

$$\Psi = \iint_S \vec{B} \cdot d\vec{S}$$

$$-\frac{d}{dt} \iint_S \vec{B} \cdot d\vec{S} = \oint_C \vec{E} \cdot d\vec{\ell}$$

$$\nabla \times \vec{E} = -\frac{\partial \vec{B}}{\partial t}$$

$$\oint_C \vec{E} \cdot d\vec{\ell} = \varepsilon$$

$$\varepsilon = \frac{W}{q} = \oint_C \frac{\vec{F}}{q} \cdot d\vec{\ell}$$

$$\Psi = LI$$

$$\varepsilon = IR$$

$$v = \frac{\omega}{\beta} = \lambda f = \frac{1}{\sqrt{\mu\epsilon}}$$

$$\omega = 2\pi f = \frac{2\pi}{T}$$

$$\eta = \frac{\sqrt{\mu}}{\sqrt{\epsilon}}$$

$$\beta = \omega\sqrt{\mu\epsilon}$$

$$\nabla^2 \vec{E} = \mu\epsilon \frac{\partial^2 \vec{E}}{\partial t^2}$$

$$\vec{S} = \vec{E} \times \vec{H}$$

$$\vec{S} = \vec{E} \times \vec{H}^*$$

$$\langle \vec{S} \rangle = \frac{1}{2} \text{Re}\{\vec{E} \times \vec{H}^*\}$$

$$\frac{\partial}{\partial t} \left(\frac{1}{2} \epsilon \vec{E} \cdot \vec{E} + \frac{1}{2} \mu \vec{H} \cdot \vec{H} \right) + \nabla \cdot \vec{S} + \vec{J} \cdot \vec{E} = 0$$

$$Q = CV$$

$$G = \frac{\sigma}{\epsilon} C \quad R = \frac{1}{G}$$

$$\vec{J}_b = \frac{\partial \vec{P}}{\partial t} + \nabla \times \vec{M}$$

$$\vec{H} = \frac{\vec{B}}{\mu_0} - \vec{M}$$

$$\vec{M} = \chi_m \vec{H}$$

$$\vec{B} = \mu_0 \mu_r \vec{H} = \mu \vec{H}$$

$$A \cos(\omega t - \beta x) \hat{z} \leftrightarrow A e^{-j\beta x}$$

$$\hat{n} \cdot (\vec{B}_1 - \vec{B}_2) = 0$$

$$\hat{n} \times (\vec{H}_1 - \vec{H}_2) = \vec{J}_s$$

$$\hat{n} \times (\vec{M}_1 - \vec{M}_2) = \vec{J}_{b,s}$$

Midterm 3 equations, in one place

	Condition	β	α	$ \eta $	τ	$\lambda = \frac{2\pi}{\beta}$	$\delta = \frac{1}{\alpha}$
Perfect dielectric	$\sigma = 0$	$\omega\sqrt{\epsilon\mu}$	0	$\sqrt{\frac{\mu}{\epsilon}}$	0	$\frac{2\pi}{\omega\sqrt{\epsilon\mu}}$	∞
Imperfect dielectric	$\frac{\sigma}{\omega\epsilon} \ll 1$	$\sim \omega\sqrt{\epsilon\mu}$	$\beta\frac{1}{2}\frac{\sigma}{\omega\epsilon} = \frac{\sigma}{2}\sqrt{\frac{\mu}{\epsilon}}$	$\sim \sqrt{\frac{\mu}{\epsilon}}$	$\sim \frac{\sigma}{2\omega\epsilon}$	$\sim \frac{2\pi}{\omega\sqrt{\epsilon\mu}}$	$\frac{2}{\sigma}\sqrt{\frac{\epsilon}{\mu}}$
Good conductor	$\frac{\sigma}{\omega\epsilon} \gg 1$	$\sim \sqrt{\pi f\mu\sigma}$	$\sim \sqrt{\pi f\mu\sigma}$	$\sqrt{\frac{\omega\mu}{\sigma}}$	45°	$\sim \frac{2\pi}{\sqrt{\pi f\mu\sigma}}$	$\sim \frac{1}{\sqrt{\pi f\mu\sigma}}$
Perfect conductor	$\sigma = \infty$	∞	∞	0	-	0	0

$$v = \frac{\omega}{\beta} = \lambda f$$

$$\nabla^2 \tilde{E} = (j\omega\mu)(\sigma + j\omega\epsilon)\tilde{E}$$

$$\Gamma = \frac{\eta_2 - \eta_1}{\eta_2 + \eta_1}$$

$$\tau = \frac{2\eta_2}{\eta_2 + \eta_1} = 1 + \Gamma$$



Units

Charge Q : C

Current I : A

Electric field strength $\vec{E}$: N/C or V/m

Electric flux density $\vec{D}$: C/m²

Polarization field $\vec{P}$: C/m²

Electric potential V : V

Capacitance C : F

Magnetic flux density $\vec{B}$: T or Wb/m²

Magnetic field strength $\vec{H}$: A/m

Magnetic flux Ψ : Wb

Electromotive force ε : V

Inductance L : H

Electric permittivity ϵ : F/m

Magnetic permeability μ : H/m

Conductivity σ : Si/m

Charge density ρ : C/m³

Surface charge density ρ_s : C/m²

Current density $\vec{j}$: A/m²

Intrinsic impedance η : Ohm

Wave number β : rad/m